
WIFI WALL SMART SWITCH /SOCKET



User Guide
UK

1 WiFi Smart Switch
Working Voltage:AC 110-240V (50/60Hz)
Normal Load Power: ≤800W
Maximum peak current:10A
Maximum peak power:1100W
Wireless Protocol:WiFi 2.4GHz
Wireless standard:IEEE802.11 b/g/n

1.1 Installation Guide



1.1.1 Installation Method



1.1.2 Touch switch installation method



1.1.3 Modified installation method after touch switch



1.2 Recovery reset status operation instructions:
1. Press the button for 20 seconds.
2. The signal indicator light will flash quickly or slowly

2 WiFi Smart Socket
Working Voltage:AC 110-240V (50/60Hz)
Normal Load Power: ≤3000W
Output:16A(Max)
Maximum peak power:3600W
Wireless Protocol:WiFi 2.4GHz
Wireless standard:IEEE802.11 b/g/n

2.1 Installation Guide



2.1.1 Installation Method



2.1.2 Touch switch installation method and retrofit installation method Refer to 1.1.2 and 1.1.3 above

2.2 Recovery reset status operation instructions:
1. Press the button for 5 seconds.
2.the signal indicator light will flash quickly or slowly

3.Download and Install App
Use your phone to scan the QR code below or search" Smart Life"from Apple store or Google play to download the APP.


Input account name and password to log in.
If you don't have an account, please register anaccount first. System will identify your country automatically. You can use your mobile phone number or Email address as your account name.

Tap on "Next " to get a verification code via SMS on your mobile phone. Enter a desired password. Tap on"Confirm" to finish your registration.



4 1 Add New WiFi Device
①Connect your phone to local wifi first
②Press the switch button for 20 seconds and till the lights flashes to reset.
③On the Smart Life APP, tap on "+"in homepage Select"Wall Switch"
④Input wifi password and confirm
⑤Wait for successful configuration

4 2 Add New Zigbee Device
1. Be sure to confirm that the device is in the fast flashing state
2. Open the tuya Zigbee smart gateway
3. In the Zigbee smart gateway, click to add a sub-device
4. Discover the device and add it, the addition is successful



5.Control on App
After successful configuration,you can control wifi switch/socket on App. You can open/close the switch/socket.


6.Set Timer
You can set a schedule to open/close your switch/socket



7.Share Device
①Select"Device Sharing"in Profile
②Tap on "Add"
③Input the cell phone number/email you want to share with
④Device will automatically be listed in your shared account

8.Manually reset the curtain switch
Repeat step5 to reset the device

9.How to control device by Amazon Alexa
Open the"Amazon Alexa" APP. Go to "Home" and select "Skills". Input "Smart Life" in the search bar. Tap on "Enable" to add the skill. Enter your "Smart Life"APP account name and password. Then tap on"Link Now" to continue. After the link succeeds, close the window and go back on the Alexa APP.






Tap on"Smart Home", select "Devices" and then tap on "Discover". Alexa will discover devices. After about 20 seconds, the devices will show in the list.



Now you can use your Alexa to voice control your Smart devices. "Alexa,turn on/off bedroom switch/socket."

10.How to control device by Google Home
Open the"Google Home" or "Google Assistant " APP. Go to "Home" and select "Home Control". Tap on "+" on the lower right corner to add skill. You can find "Smart Life" in "Add devices" list.



Select your country code. Enter your "Smart Life"APP account name and password. Then tap on"Link Now" to continue.After the link succeeds, you can assign rooms for your smart devices. Later you can find the smart devices in the Home Control list.



Now you can use your Google Home to voice control your Smart devices.
"Ok, Google,turn on/off bedroom switch/socket ."

WIFI WALL SMART SCHALTER / STECKDOSE

Bedienungsanleitung
DE

1 WiFi Smart Schalter
Working Voltage:AC 110-240V (50/60Hz)
Normal Load Power: ≤800W
Maximum peak current:10A
Maximum peak power:1100W
Wireless Protocol:WiFi 2.4GHz
Wireless standard:IEEE802.11 b/g/n

1.1 Installationsanleitung

1.1.1 Installationsmethode

1.1.2 Installationsmethode für den Touch-Switch

1.1.3 Geänderte Installationsmethode nach Berührungsschalter

1.2 Anweisungen zum Zurücksetzen des Wiederherstellungsstatus:
1. Drücken Sie die Taste 20 Sekunden lang.
2. Die Signalanzeige blinkt schnell oder langsam

2 WiFi Smart Stechdose
Working Voltage:AC 110-240V (50/60Hz)
Normal Load Power: ≤3000W
Output:16A(Max)
Maximum peak power:3600W
Wireless Protocol:WiFi 2.4GHz
Wireless standard:IEEE802.11 b/g/n

2.1 Schaltplan

2.1.1 Installation Method

2.1.2 Installationsmethode des Touch-Schalters und NachrüstungInstallationsmethode Siehe 1.1.2 und 1.1.3 oben

2.2 Anweisungen zum Zurücksetzen des Wiederherstellungsstatus:
1. Drücken Sie die Taste 5 Sekunden lang.
2. Die Signalanzeige blinkt schnell oder langsam

3.APP Herunterladen and Installieren
Scannen Sie den QR-Code mit Ihrem Handy oder suchen Sie nach „Smart Life" im Apple Store oder Google Play, um die APP herunterzuladen.

Geben Sie den Kontonamen und das Passwort zum Einloggen ein.
Erstellen Sie Ihr Konto bitte zuerst, wenn Sie noch kein Konto haben. Ihr Land wird vom System automatisch erkannt. Sie können Ihre Handynummer oder Email-Adresse als Kontonamen verwenden.

Tippen Sie auf „Weiter", dann werden Sie einen Bestätigungscode per Nachrichten auf Ihrem Handy erhalten. Geben Sie ein gewünschtes Passwort ein. Tippen Sie auf „Bestätigen" zum Beenden Ihrer Registrierung.

4.1 Neues Gerät Hinzufügen
① Verbinden Sie Ihr Handy zuerst mit dem lokalen WiFi
② Halten Sie die "Ab"-Taste für 20 Sekunden gedrückt, bis die Anzeige schnell blinkt
③ In der „Smart Life"-APP tippen Sie auf der Startseite auf "+"
④ Wählen Sie "Wandschalter"
⑤ Geben Sie Wifi Passwort ein und bestätigen
⑥ Warten Sie auf eine erfolgreiche Konfiguration

4.2 Neues ZigBee-Gerät hinzufügen
1. Stellen Sie sicher, dass sich das Gerät im schnell blinkenden Zustand befindet
2. Öffnen Sie das Tuya ZigBee Smart Gateway
3. Klicken Sie im ZigBee Smart Gateway auf, um ein Untergerät hinzuzufügen
4. Entdecken Sie das Gerät und fügen Sie es hinzu.
Das Hinzufügen ist erfolgreich

5.APP Steuern
Nach erfolgreicher Konfiguration können Sie den WiFi-Schalter / Steckdose in der App steuern. Sie können den Schalter / Steckdose öffnen/schließen.

6.Timer Einstellen
Sie können einen Zeitplan für das Öffnen/Schließen vom Schalter / Steckdose.

7.Gerät Teilen
*Wählen Sie „Gerät Teilen" im Profil
*Tippen Sie auf „Hinzufügen"
*Geben Sie die Handynummer/Email-Adresse ein, mit der Sie teilen möchten
*Das Gerät wird automatisch in Ihrem geteilten Konto aufgelistet

8.Vorhangschalter Manuell Zurücksetzen
Wiederholen Sie Schritt 5 zum Zurücksetzen des Geräts

9.Gerät von Amazon Alexa Steuern
Öffnen Sie die „Amazon Alexa"-APP. Gehen Sie zur „Startseite" und wählen Sie „Fähigkeiten". Geben Sie „Smart Life" in die Suchleiste ein. Dann geben Sie Ihren APP-Kontonamen und das Passwort ein. Tippen Sie anschließend auf „Jetzt verbinden" zum Fortsetzen. Nach erfolgreicher Verbindung schließen Sie das Fenster und gehen Sie zurück zur Alexa-APP.

Tippen Sie auf „Smart Home", wählen Sie „Geräte" und tippen Sie anschließend auf „Entdecken". Dann wird Alexa Geräte entdecken. Nach ca. 20 Sekunden werden die Geräte in der Liste angezeigt.

Jetzt können Sie durch Alexa Ihre intelligente Geräte sprachsteuern."Alexa, Schalter / Steckdose."

10.Gerät von Google Home Steuern
Öffnen Sie die APP von „Google Home" oder „Google Assistant". Gehen Sie zur „Startseite" und wählen Sie „Haussteuerung". Tippen Sie in der rechten unteren Ecke auf „+" zum Hinzufügen der Fähigkeiten. Sie können „Smart Life" in der Liste „Geräte hinzufügen" finden.

Wählen Sie Ihren Ländercode. Geben Sie Ihren APP-Kontonamen und das Passwort ein. Tippen Sie anschließend auf „Jetzt Verbinden" zum Fortsetzen. Nach der erfolgreichen Verbindung können Sie Ihren intelligenten Geräten Räume zuweisen. Später werden Sie die intelligenten Geräte in der Haussteuerung-Liste finden.

Jetzt können Sie durch Google Home Ihre intelligente Geräte sprachsteuern. "Alexa, Schalter / Steckdose."